



single branch unit series

- > Voice, Data, Video capable
- > Internal isolation jumpers
- > Terminal and Saddle connections
- > Intrinsic Safe version
- > IP66/NEM4X enclosure



DESCRIPTION

BU1 Single branch unit series, is a passive device used to branch off (one Input – 2 Outputs) the main cable into a side tunnel or into another level. The BU1 has been designed to provide a balanced RF output, with a minimum attenuation loss through the branch. The branch will also pass a DC voltage to power the down line amplifiers with minimal voltage drop.

The BU1 utilises MineCom's proprietary leaky feeder terminal and saddle connections (rather than coaxial connectors which can cause higher losses and voltage drops), designed for easy assembly underground without the need for special tools or skills.

The BU1 is also equipped with isolating jumpers, which will allow mine staff to:

- > Isolate/terminate the branch. (Blocks both RF and DC from entering the branch cable)
- > DC Isolate the branch. (Blocks DC from entering the branch cable)
- > Passes both RF and DC to the branch. (Normal operation)

SPECIFICATIONS

Frequency:	VHF & UHF
Insertion Loss:	4dB (VHF); 5dB (UHF)
Impedance:	75 ohm
VSWR:	1.4:1 (148 – 175Mhz) 1.2:1 (20 to 120Mhz)
Through Current Capacity:	1.5 amps Max
Power Requirements:	None
Connections:	Proprietary - Brass Screw terminal and Saddle (optional N type)
Enclosure:	IP66/NEMA4X heavy duty enclosure
Weight & Dimensions:	1.0Kg - 160(w) x 60(d) x 75(h)mm

LOCATIONS ACROSS AUSTRALIA,
NEW ZEALAND & MALAYSIA

For all your mining communications call

+61 3 9896 3000

or email sales@minecom.com

TR Corporation Pty Ltd

6 Joseph Street (PO Box 1185)
Blackburn North VIC 3130
AUSTRALIA

ABN: 99 005 499 721

www.minecom.com